1050X





**Philips Domestic Appliances and Personal Care** 

# ServiceManual

### **PRODUCT INFORMATION**

### General:

- Rechargeble
- World wide automatic voltage selection
- Washable
- Charge indication
- Battery low indication
- Battery full indication
- Travel lock
- Cleaning indicator
- Charge indicator
- Shaving unit replacement indicator

# Safety info

- This product meets the requirements regarding interference suppression on radio and TV.
- After the product has been repaired, it should function properly and has to meet the safety requirements as officially laid down at this moment.

# **TECHNICAL INFORMATION**


- Voltage : 100 - 240 V / 50 - 60 Hz - Shaving unit : RQ10 (4222 036 15000)

Charging time : 1 hourShaving time : up to 21 day'sSAP coding : 1050X

**PHILIPS** 

# **DISASSEMBLY- AND RE-ASSEMBLY ADVICE**

- Remove shaving unit to prevent damaging during repairing
- Remove pivot cap (pos 3) with a little knife
- Remove screws A




- Remove cover (pos 12)

Start on trimmerside

push left on the housing and right on the cover and make a smal opening



now push right on the housing and left on the cover so you can remove the cover.




- Remove side grip's
- Remove housing shell (pos 4) start on trimmer side
- Remove deco plate assy (pos 7) snaplock on the side
- Remove screws B
- Remove pivot base (pos 8)
- Remove trimmer

# **REPAIR INSTRUCTIONS**

- No specific issues

# **OPTIONAL** (accessories)

- 4222 036 02770 Brush black
- 4222 036 05160 Power plug U1 Str. NOR
- 4222 036 15120 Powerpod HE SR1



- 4222 036 15020 Stand HE



- 4222 036 15150 Jet clean III HE



## **PARTS LIST**

Pos	Service code	Description
1	4222 036 14990	Protection cap
2	4222 036 15000	Shaving unit SR1
3	4222 036 15080	Pivot cap SR1
4	4222 036 15100	Housing shell SR1 LE
5	4222 036 15050	Basic body SR1 LE
6	4222 036 14950	Magnet SR1
7	4222 036 15280	Deco Plate assy SR1 LE
8	4222 036 14980	Pivot base SR1
9	4222 036 15010	Trimmer assy SR1 HE/LE (Black knob)
10	4222 036 14940	Pivot Release spring SR1
11	4222 036 14970	Sidepanel (L+R) SR1 ME/LE
12	4222 036 15060	Cover shell SR1 HE/LE
	4222 036 03540	Screw A (Black)
	4822 502 14545	Screw B

EXPLODED VIEW 1050X

